

Uninterruptible Power Supply Unit for Universal Use QUINT-DC-UPS/24DC/10

harland simon
power solutions



1. Short Description

Uninterruptible Power Supply Units for Buffering Long-Term Power Interruptions

- Saves space thanks to the compact, uniform design
- Integrated diode saves money through isolation of loads
- Maximum system availability through optimum battery management and reliable signaling
- Minimum installation time due to ready-to-use plug-in bridges and integrated timeout

QUINT-DC-UPS uninterruptible power supply units with long-life lead-acid batteries provide long buffer times at high currents. Even in the event of a longer supply voltage failure, the units ensure that all connected devices continue to operate without interruption.

The devices have a narrow and uniform design, which makes them ideal for use on the DIN rail where space is limited. In addition, short wiring paths ensure order and clarity in the control cabinet.

The high level of availability and the particularly long service life of the battery modules are achieved through professional battery management. An automatic presence check (every minute) and electronic overcurrent protection ensure the battery modules are ready to operate at all times. Power is therefore available in the event of an error and the service life of the battery module is maximized.

The actual state must be determined quickly so that the right decision can be made in an emergency. Optimum signaling is thus required for maximum system availability. Three floating PDT contacts and three LEDs are provided for function monitoring, which indicate all the operating states clearly.

So that relay signaling is more reliable and more durable than before, an additional positive supply output has been provided. The contact, which is current-limited and resistant to continued short circuits, is located next to the relay connections and enables easy bridging. In the event of wiring errors, the short-circuit protection prevents any welding of the relay contacts. This ensures that the user can rely on an OK signal. Even in the event of connection errors, currents remain below 100 mA, which prevents damage to the relay contacts.

A system is switched off after a specific time that can be set on the device or by an external signal. No additional installation is required for shutdown. In



addition, ready-to-use plug-in bridges minimize the installation time.



The connected devices can be divided into buffered and unbuffered loads using the isolated input. This extends the buffer time, which depends on the output current. If only critical devices are protected using fuses, smaller battery modules can be used that save money and space in the control cabinet. In addition, the isolated input protects the connected devices against errors in the internal network.

harland simon
power solutions



enquiries@hsups.co.uk • +44 1908 565656 • harlandsimonups.com
Harland Simon UPS Ltd • Bond Avenue • Bletchley • MK11 1TJ

2. Technical Data



QUINT-DC-UPS/24DC/10

	Solid [mm ²]	Stranded [mm ²]	Torque AWG	[Nm]	[lb in]
Input	0.2 - 2.5	0.2 - 2.5	25 - 14	0.5 - 0.6	4.4 - 5.3
Output	0.2 - 2.5	0.2 - 2.5	25 - 14	0.5 - 0.6	4.4 - 5.3
Signal	0.2 - 2.5	0.2 - 2.5	25 - 14	0.5 - 0.6	4.4 - 5.3

Description

Uninterruptible power supply unit
with integrated 1.3 Ah battery module

DC UPS module

Type	Order No.	Pcs. Pkt.
QUINT-DC-UPS/24DC/10	28 66 22 6	1

Technical Data

Input Data

Nominal input voltage	24 V DC
Input voltage range	22.5 - 30 V DC
Current consumption	(No load/charging/maximum)
Switching threshold	0.1 A/0.5 A/10.5 A
Buffer time	configurable
Input fuse	
Maximum power dissipation	(Ready/buffer mode)

24 V DC
22.5 - 30 V DC
0.1 A/0.5 A/10.5 A
 $U_a < 22$ V; dynamic $U_{in} - 1$ V/0.1 s
0.5, 1, 2, 3, 10, 15, 20, 30, continuous
Internal, 15 A
20 W/8 W

Output Data

Can be connected in parallel

No

Output Data in Normal Operation

Nominal output voltage	24 V DC
Output voltage	U_{in}
Output current	10 A
Current limit	None
Overload fuse	Internal, 15 A

24 V DC
 U_{in}
10 A
None
Internal, 15 A

Output Data in Buffer Mode

Nominal output voltage	24 V DC
Output voltage	27.9 V DC, maximum
Output current	10 A
Current limit	15 A
Overload fuse	15 A, internal fuse
Efficiency	91%
Remote shutdown	Yes

24 V DC
27.9 V DC, maximum
10 A
15 A
15 A, internal fuse
91%
Yes

Charging

Charge characteristic curve	I/U characteristic curve
End-of-charge voltage	27 V
Charge current	400 mA
Temperature/voltage compensation	No
Battery/presence check/time interval	60 seconds

I/U characteristic curve
27 V
400 mA
No
60 seconds

Memory Medium

Nominal voltage	Internal
Nominal capacity	24 V DC
Service life	1.3 Ah
Self-discharge	6 years at +20°C
Latest startup after delivery	< 1 mA

Internal
24 V DC
1.3 Ah
6 years at +20°C
< 1 mA
9 months at +20°C to +30°C
6 months at +30°C to +40°C

Uninterruptible Power Supply Unit for Universal Use – QUINT-DC-UPS/24DC/10

Signaling	
Power In OK	Green LED
Alarm	Red LED, floating PDT, 30 V AC/DC, maximum; 1 A, maximum
Battery Mode	Yellow LED, floating PDT, 30 V AC/DC, maximum; 1 A, maximum
Battery Charge	Yellow LED, flashing, floating PDT, 30 V AC/DC, maximum; 1 A, maximum

Approvals/Standards	
Electrical equipment of machines	EN 60 204 (Surge Voltage Category III)
Electrical safety (of IT equipment)	EN 60 950/VDE 0805, UL/C-UL Recognized UL 60 950
Industrial control equipment	UL/C-UL Listed UL 508
Shipbuilding	Germanischer Lloyd
Electronic equipment for use in electrical power installations	EN 50 178 (VDE 0160)

General Data	
Insulation voltage	Input/output to housing: 1 kV AC type test 1 kV AC routine test On a horizontal 35 mm DIN rail
Mounting position	EN 60 715 1 kV/1 kV IP20 II
Degree of protection	> 500,000 h
Class of protection	AluNox (AlMg1), closed
MTBF	According to IEC 1709 (SN 29 500)
Housing version	(100 x 130 x 125) mm
Dimensions (W x H x D) default upon delivery	Approximately
Weight	1.8 kg

Climatic Data	
Ambient temperature	Operation/storage 0°C to +50°C/0°C to +40°C
Humidity	At +25°C 95%, no condensation
Vibration	According to IEC 68-2-6 15 Hz - 150 Hz, 2.3g, 90 minutes
Shock (in all space directions)	According to IEC 68-2-27 30g
Pollution degree	According to EN 50 178 2
Climatic category	According to EN 60 721 3K3



Conformance With EMC Directive 89/336/EEC
and Low Voltage Directive 73/23/EEC

EMC (Electromagnetic Compatibility) Noise Immunity According to EN 61000-6-2:	Requirements EN 61 000-6-2	QUINT-DC-UPS/24DC/10
Noise Immunity According to EN 61000-6-2		
• EN 61000-4-2 ³⁾ Electrostatic discharge (ESD)	Housing Contact discharge: Air discharge:	4 kV 8 kV 15 kV Level 4 8 kV 15 kV Level 4
• EN 61000-4-3 ²⁾ Electromagnetic HF field	Housing Frequency Field strength:	80 - 1000 MHz 10 V/m Level 3 80 - 1000 MHz/1.4 - 2.0 GHz 10 V/m Level 3
• EN 61000-4-4 ³⁾ Fast transients (burst):	Input Output Signal:	2 kV 2 kV 1 kV asymmetrical ⁽⁵⁾ asymmetrical ⁽⁵⁾ asymmetrical ⁽⁵⁾ 4 kV (Level 4) 2 kV (Level 3) 1 kV (Level 2) Level 3
• EN 61000-4-5 ³⁾ Surge current loads (surge):	Input: Output: Signal:	2 kV 2 kV 0.5 kV 0.5 kV 1 kV asymmetrical ⁽⁵⁾ symmetrical ⁽⁴⁾ asymmetrical ⁽⁵⁾ symmetrical ⁽⁴⁾ asymmetrical ⁽⁵⁾ 4 kV (Inst. Class 4) 2 kV (Inst. Class 4) 0.5 kV/(Level 1) 0.5 kV/(Level 1) 1 kV/(Level 2) Level 3
• EN 61000-4-6 ²⁾ Conducted interference	I/O/S: Frequency: U ₀ :	asymmetrical ⁽⁵⁾ 0.15 - 80 MHz 10 V Level 3 0.15 - 80 MHz 10 V Level 3
• EN 61000-4-11 ³⁾ Voltage dips	Input:	30% reduction of the input voltage for 0.5 periods See Input Data: Mains buffering > 20 ms
Noise Emission According to EN 61000-6-3	Class A ⁽⁶⁾ Class A ⁽⁶⁾	EN 55011 (EN 55022) Class B ⁽⁷⁾ EN 55011 (EN 55022) Class B ⁽⁷⁾

EN 55011 corresponds to CISPR11/EN 55022 corresponds to CISPR22/EN 61000 corresponds to IEC 1000

2) Criterion A: Normal operating characteristics within the specified limits.

3) Criterion B: Temporary adverse effects on the operating characteristics which the device corrects automatically.

⁴⁾ Symmetrical: Cable to cable.

⁵⁾ Asymmetrical: Cable to ground.

⁶⁾ Class A: Industrial applications

⁷⁾ Class B: Industrial and domestic applications.

3. Device View, Connections, and Control Elements




Figure 04

- ① DC input, unbuffered:
24 V DC input voltage
(0.2 mm² to 2.5 mm² solid)
(0.2 mm² to 2.5 mm² stranded)
(25 - 14 AWG)
Internal fuse only 15 A
- ② DC output, buffered:
24 V DC output voltage
(0.2 mm² to 2.5 mm² stranded) (25 - 14 AWG)
The device is idling-proof and short-circuit-proof.
- ③ Floating PDT (11,12,13): Alarm
- ④ Floating PDT (21,22,23): Battery Mode
- ⑤ Floating PDT (31,32,33): Battery Charge
- ⑥ 24 V supply voltage, maximum current limit
0.2 A for grouped contacts 11, 21, 31
- ⑦ Remote shutdown (R1, R2)
- ⑧ Universal DIN rail adapter UTA 107
- ⑨ Red LED: Alarm
- ⑩ Yellow LED: Battery Mode/
Battery Charge
- ⑪ Green LED: Power In OK
- ⑫ Buffer time setting 0.5 - 30 minutes

4. Safety Notes and Warning Instructions

To ensure that the device can be operated safely and all functions can be used, please read these instructions carefully.

The QUINT-DC-UPS is a built-in device. **Installation and startup** must only be carried out by qualified personnel. The relevant country-specific regulations (e.g., VDE, DIN) must also be observed.

Before startup it is particularly important to ensure that:

- All supply lines have sufficient fuse protection and are the correct size.
- All output cables are the correct size for the maximum device output current or have separate fuse protection.
- Sufficient convection is ensured.

5. Installation

The uninterruptible power supply unit can be snapped onto all DIN rails according to EN 60715 and should be mounted horizontally (input terminal blocks facing downwards).

Installation Dimensions




Figure 05

5.1. Mounting

Place the module with the DIN rail guideway on the **top edge** of the DIN rail and then snap it **downwards**.

5.2. Removal

Release the snap-on catch using a screwdriver and then detach the module from the **bottom edge** of the DIN rail.




Figure 06




Figure 07


5.3. Connection:

The device is equipped with COMBICON connectors. This reliable user-friendly connection method enables quick device connection and visible isolation of the electrical connection, if required. **Only operate connectors when the power is switched off.**

The following cable cross sections can be connected:

	Solid [mm ²]	Stranded [mm ²]	AWG	Torque [Nm]
① Input:	0.2 - 2.5	0.2 - 2.5	25 - 14	0.5 - 0.6
② Output:	0.2 - 2.5	0.2 - 2.5	25 - 14	0.5 - 0.6
③ ⑦ Signal:	0.2 - 2.5	0.2 - 2.5	25 - 14	0.5 - 0.6

For reliable and safe-to-touch connections: Strip 7 mm from the connector ends.



To maintain UL approvals, use copper cables, which are designed for operating temperatures > +75°C. To meet GL requirements, unused terminal compartments should be closed.

5.4. Input (①, Figure 04, Figure 08)

The QUINT-DC-UPS is connected to the 24 V DC output of the power supply via the "Input +" and "Input -" terminal blocks. The output is isolated from the input by the internal diode. The stored power is only supplied to the output. The device is protected against overcurrent and short circuit by a 15 A internal input fuse. If the power supply unit supplies a higher current, e.g., QUINT POWER 24V/20A, a backup fuse must be used, which is designed for the nominal current of the DC-UPS.




Figure 08

Fuse

Further device protection is not required, as an internal fuse is present.



If the internal fuse is blown, this is most probably due to a device fault. In this case, the device should be checked in the factory.

5.5. Output (② Figure 04, Figure 07)

All devices that must be supplied without interruption in the event of a supply voltage failure ("Buffered Load"), are connected to the "Output +" and "Output -" terminal blocks of the DC output (Fig. 07). It is recommended that all other loads, which do not require buffering ("Unbuffered Load"), are connected to the 24 V DC output of the power supply.

This increases the buffer time, as this time depends on the output current (see Fig. 09). The internal diode ensures that the buffered loads are isolated from the unbuffered loads.

5.6. Signaling Outputs

The signal outputs are connected via terminal blocks 11/12/13 ③, 21/22/23 ④ or 31/32/33 ⑤. The contacts are floating contacts. The plug-in bridge provided can be used to supply +24 V to grouped contacts 11,21,31. This means that signal outputs 12, 13, 22, 23, 32, 33 can be evaluated as switching outputs with 0 V and +24 V voltage levels.

5.7. Remote Shutdown ("Remote", Fig. 10)

The device has a UPS remote shutdown function for specific shutdown.

Remote shutdown must be deactivated for the device to switch to buffer mode in the event of a supply voltage failure.

Remote Shutdown Off

- The "Remote shutdown R1" and "Remote shutdown R2" terminal points are short circuited (e.g., with a plug-in bridge) OR The "Remote shutdown R2" terminal point is supplied with a 24 V DC voltage
- The QUINT-DC-UPS switches to buffer mode in the event of a supply voltage failure

Remote Shutdown On

- The "Remote shutdown R1" and "Remote shutdown R2" terminal points are not connected
- All LEDs are off
- The QUINT-DC-UPS does not switch to buffer mode in the event of a supply voltage failure, instead the device is shut down. When the supply voltage is reapplied, the battery module is charged and the device remains off until remote shutdown is deactivated.
- Connected loads are supplied as long as the supply voltage is present

6. Setting Options on the Device

6.1 Buffer Time Setting (Figure 11)

Buffer mode can be exited after a predefined time has elapsed or by external shutdown (see 6.7). If the device is to be shut down after a specific time has elapsed, the time can be set via the selector switch ⑫ on the front of the device. When the supply voltage is reapplied, the device can switch to buffer mode again.




Figure 09




Figure 10




Figure 11

7. Method of Operation

In the event of a power failure at the output, the QUINT-DC-UPS supplies all connected devices with a 24 V DC voltage without interruption at a load current up to 10 A. When the 24 V supply voltage is applied, the connected battery module is charged. In the event of a supply voltage failure, the battery module is connected to the output, and the stored power ensures that all connected devices continue to operate without interruption. The professional signaling via function LEDs and floating PDT contacts enables reliable evaluation of all the main operating states.

7.1. Output Voltage

In normal operation, the QUINT-DC-UPS output voltage corresponds to the usual supply voltage. If the supply voltage drops more than 1 V in the space of 0.1 seconds or falls below the minimum threshold of 22 V, the device switches to buffer mode.

If the output voltage drops below 20.4 V in buffer mode, this is indicated by the Alarm indicator.

If the output voltage drops to 19.2 V because the battery module is flat, the device is shut down completely.

When the supply voltage is reapplied, the device automatically switches on again. The device is electronically short-circuit-proof and idling-proof.

7.2. Signaling

Three floating PDT contacts and three indicators are provided for function monitoring. If the floating contacts are supplied externally with +24 V, they can also be used as 24 V switching outputs.

Key/Indicators	Green ^⑪ Power IN OK	Yellow ^⑩ Bat. Mode/Charge	Red ^⑨ Alarm
Supply voltage OK, battery module charging	ON	Flashing	OFF
Supply voltage OK, battery module charged (normal operation)	ON	OFF	OFF
Buffer mode	OFF	ON	OFF
Battery module flat	OFF	OFF	ON
- Battery module quality test negative - Service	ON	OFF	ON
- Buffer time elapsed - Remote shutdown activated	OFF	OFF	OFF

xx - xx: Contact closed,

1x Alarm, 2x Battery Mode, 3x Battery Charge
x1 group contact, x2 N/C contact, x3 N/O contact

Key/Output	Bat. Charge ^⑤	Bat. Mode ^④	Alarm ^③
Supply voltage OK, battery module charging	31 - 33	21 - 22	
Supply voltage OK, battery module charged (normal operation)	31 - 32	21 - 22	
Buffer mode	31 - 32	21 - 23	
Battery module flat	31 - 32	21 - 22	11 - 13
- Battery module quality test negative - Service	31 - 32	21 - 22	11 - 13
- Buffer time elapsed - Remote shutdown activated		21 - 22	11 - 13